
Technical features

Pressure range	010 mbar up to 035 bar	Linearity	± 0.15% FS
• Input signal	010 V and 420 mA	Hysteresis	± 0.15% FS
Security	constant outlet pressure at voltage drop	 Response sensitivity 	< 0.1% FS
Response time	10 to 15 ms	 Repeatability 	± 0.02% FS
Adjustment	zero point and span	 Protection class 	IP 65



General technical features

Sensitivity

Description Two solenoid valves control the system pressure. One valve is for inlet control, the other for

outlet control. A strain gauge pressure transducer measures system pressure and provides a feedback signal to the electronic controls. Any difference between command and feedback signals causes one of the solenoid valves to open, causing system pressure to increase or

Air consumption

without constant bleed

decrease.

Mounting position any, immune to shock and vibration up to 25 g

Protection class IP 65 housing

Temperature range -5 °C to 70 °C / 23 °F to 158 °F

Material Body: aluminium Elastomer: FKM

immune to shock and vibration up to 25 g

Transducer: aluminium and silicon Valves: nickel-plated brass

Pneumatic features

Media dry, unlubricated and 5 μm filtered compressed air or non-corrosive gases

Supply pressure see chart, minimum 10% above outlet pressure

Flow rate 35 l/min at 7 bar supply pressure and open outlet, optionally 100 l/min

3 l/min at controlled outlet pressure

Exhaust same nominal size as on inlet valve, thus same relief capacity

Air consumption without constant bleed, Option X58: < 2 l/min

Electrical features

Supply voltage 15 ... 24 V DC, reverse voltage protection existing

Power consumption 3.6 W for regulation, 0.5 W non-regulating

 $\begin{tabular}{ll} \textbf{Signal range} & 0 \dots 10 \ V, \ \textbf{optionally} \ 4 \dots 20 \ \textbf{mA} \\ \end{tabular}$

 $\label{eq:continuous} \mbox{Impedance} \qquad \qquad 4.7 \ \mbox{k} \Omega \quad \mbox{at voltage signal}, \quad 100 \ \Omega \quad \mbox{at current signal}$

10 k $\!\Omega\!$ at voltage signal, $\,$ 100 $\!\Omega\!$ at current signal, for external feedback

 $\label{eq:monitor signal impedance } \mbox{ > 4.7 k} \mbox{ } \mbox{k} \mbox{ } \mbox{at voltage signal, } \mbox{ } \mbox{ } \mbox{<100 } \mbox{ } \mbox{0} \mbox{ } \mbox{at current signal } \mbox{ }$

Electrical connector plug M16x0.75, 7-pin, with coupling socket

Monitor signal 0 ... 10 V, optionally 4 ... 20 mA

Security constant outlet pressure at voltage drop

Accuracy

 $\begin{array}{lll} \mbox{Linearity/Hysteresis} & \pm \ 0.15\% \ \mbox{FS} \\ \mbox{Response sensitivity} & < 0.1\% \ \mbox{FS} \\ \mbox{Response time} & 10 \ \mbox{to} \ 15 \ \mbox{ms} \\ \mbox{Repeatability} & \pm \ 0.02\% \ \mbox{FS} \\ \end{array}$

Temperature influence < 0.01% FS per °C/K at ~0 °C to 50 °C / 32 °F to 122 °F < 1.00% FS per °C/K at 50 °C to 70 °C / 122 °F to 158 °F

Accuracy over all \pm 0.2 % FS

Regulating time < 2 s to fill 0.1 l volume to 90% of the initial pressure (or to exhaust) < 40 s to fill 2 l volume to 90% of the initial pressure (< 80 s to exhaust)

Adjustment

Zero point The zero point can be increased by up to 20% of full scale, e.g. from 0 bar to 1.2 bar


at a 6 bar regulator. External adjustment via potentiometer Z "zero".

Span The maximum pressure value of the control range can be reduced by up to 20% depending


on the selected pressure range, e.g. from 6 to 4.8 bar. External adjustment via


potentiometer S "span".


PDF CAD www.aircom.net



cross-section PQ









^{*1} at 7 bar supply pressure and 3 bar outlet pressure

Description The pneumatic proportional pressure regulator produces outlet pressure in proportion to an electrical command input signal. It comprises a complete closed loop servo system consisting of valves, manifold, housing and electronic controls.


Pressure is controlled by two solenoid valves. One valve functions as inlet control, the other as exhaust. Single loop The pressure outlet is measured by an internal pressure transducer which provides a feedback signal to the electronic controls. This feedback signal is compared with the command input signal. Any difference between the two signals causes one of the two solenoid valves to open, allowing flow into or out of the

system. Accurate pressure is maintained by these two valves.

Linearity / Hysteresis: ± 0.15% FS Response sensitivity: < 0.1% FS Accuracy

Repeatability: ± 0.02% FS Accuracy over all ± 0.2% FS

Dimensions		Flow	Supply	Accuracy	/ Connection	Pressure	Order		
Α	В	С	rate	pressure		thread	range	number	E*
mm	mm	mm	I/min*1	max. mbar/bar*	¹² %	G	mbar/bar		





Sin	gle lo	оор	regulato	r	0 1 supp	I0 V input and f ly voltage 24 V	eedback sign DC, 35 l/min*	al, ¹, with coupling sock	_{et} PQ1
51	106	8	on request	20 1	mbar mbar mbar mbar mbar mbar mbar mbar	0.2	G1/8	0 5 mbar 0 10 mbar 0 20 mbar 0 50 mbar 0 100 mbar 0 200 mbar 0 400 mbar 0 600 mbar	PQ1EE-A5 PQ1EE-B1 PQ1EE-B5 PQ1EE-C1 PQ1EE-C2 PQ1EE-C4 PQ1EE-C6
51	106	8	35	2 3 7 7 9 15 15 24 24 38 38 38	bar bar bar bar bar bar bar bar bar bar	0.2	G⅓	0 1 bar 0 2 bar 0 4 bar 0 6 bar 0 8 bar 0 10 bar 0 12 bar 0 16 bar 0 20 bar 0 25 bar 0 30 bar 0 35 bar	PQ1EE-01 PQ1EE-02 PQ1EE-04 PQ1EE-06 PQ1EE-08 PQ1EE-10 PQ1EE-12 PQ1EE-16 PQ1EE-20 PQ1EE-25 PQ1EE-30 PQ1EE-35
51	106	8	35	0 2	bar bar	0.2	G½	01 bar -1 +1 bar	PQ1EE-V0 PQ1EE-V1


Special options, add the appropriate letter or number

4-20 mA PQ1 IC-.. input and monitor signal increased flow rate, max. 10 bar, not combinable with Opt. ..X58 PQ1 . . - . . HF flow 100 I/min continuous regulation*3 improved characteristic curve through proportional inlet valve, max. 10 bar PQ1 . . - . . X58 PQ1 . . - . . **X59** declining curve inverted outlet


Accessories, enclosed


M16x0,75, 7-pin with 2 m cable PRK-A2L coupling socket straight PRK-C2L angular mounting bracket made of steel PQKT-01





 *1 at 7 bar supply pressure and open outlet, at regulated flow rate of 3 l/min
 *2 higher supply pressure on request *2 higher supply pressure on request






connection diagram for supply and signal









PROPORTIONAL PRESSURE REGULATOR WITH DOUBLE LOOP, ACCURATE TO 0.2%

Pressure

range

mhar/har

Order

number

PQ2EE-V1

-1... +1 bar

E,

Description The pneumatic proportional pressure regulator produces outlet pressure in proportion to an electrical command input signal. It comprises a complete closed loop servo system consisting of valves, manifold, housing and electronic controls.

Flow

rate

I/min*1

Supply

pressure

may mhar/har*2

The servo valve expands in single loop operation by combining an additional feedback from an external sensing device with the internal transducer. The external sensor provides information on the control status. The PQ2 then compares the command signal with the second loop feedback signal.

Should there be a difference in the signal comparisons, the servo valve will make adjustments to the internal loop to bring the system into balance. This provides accurate final outlet. The acceptance of electrical feedback from a fever real sensor enables precise control of conditions such as pressure,

External pressure transducer

Dimensions

В

mm

Α

С

mm

Double loop


Any pressure transducer for 0-10 V and 4-20 mA output signal and suitable for 15-24V DC supply

thread

C

voltage can be applied. An appropriate coupling socket plus cable is required.

Accuracy Connection



	/ bar	nbar/	n	G	%	bar/bar**	max. m	ı/mın^'	mm	mm	mm
_s PQ2	na oooko				out / feedback ge 24 V DC, 3		or	regulat	oop	ıble l	Dou
PQ2EE-A5 PQ2EE-B1 PQ2EE-B2 PQ2EE-B5 PQ2EE-C1 PQ2EE-C2 PQ2EE-C4 PQ2EE-C6	mbar mbar mbar mbar mbar mbar mbar mbar	5 r 10 r 20 r 50 r 100 r 200 r	0 0 0 0 0	G½	0.2	mbar mbar mbar mbar mbar mbar mbar mbar	t 10 i 20 i 40 i	on reques	8	106	51
PQ2EE-01 PQ2EE-02 PQ2EE-04 PQ2EE-06 PQ2EE-10 PQ2EE-12 PQ2EE-16 PQ2EE-20 PQ2EE-25 PQ2EE-30 PQ2EE-35	bar bar bar bar bar bar bar bar bar	20 25 30	0 0 0 0 0 0 0	G1/8	0.2	bar bar bar bar bar bar bar bar bar bar	2 3 7 7 9 15 15 24 24 38 38 38	35	8	106	51
PQ2EE-V0	bar	- 1	0	G½	0.2	bar	0	35	8	106	51



PQ2



combination example: booster with proportional pressure regulator and second loop via pressure transducer

Special options, add the appropriate letter or number

2 bar


4-20 mA	input / feedback / second loop signal	PQ2 IC
flow 100 I/min	increased flow rate, max. 10 bar	PQ2 HF
continuous regulation*	³ improved characteristic curve through proportional inlet valve, max. 10 bar	PQ2 X58
declining curve	inverted outlet	PQ2 X59



PRK-A PRK-C

Accessories, enclosed


coupling socket	M16x0.75,	7-pin with 2.0 m cable,	supply and signal,	•	
coupling socket	½″UNF,	3-pin with 0.9 m cable,	for second loop,	straight	PRK-C2L PQH-L1
mounting bracket	made of stee	ıl		angular	PQH-L2 PQKT-01



connection diagram for second electrical loop

PQ2 with second loop * Product group

supply



PDF CAD

www.aircom.net



transducer e. g. D2

revolution

transducer

load

 ^{*1} at 7 bar supply pressure and open outlet, at regulated flow rate of 3 l/min
 *2 higher supply pressures on request